

## ELECTROSOFT AS2225 LATEX ELECTRICAL GLOVES

### PRODUCT INFORMATION

Electrosoft Natural Latex gloves are now available with approval to Australian Standard AS2225 : 1994.

Offering the widest range of conditions for use from 650 to 4000 volts. Latex gloves possess high dielectric characteristics, making them perfect for use in many electrical applications, from low voltage to high voltage.

When used in conjunction with a leather overglove, these electrical gloves offer protection against cutting or tearing.

### PRODUCT FEATURES

- ⇒ Meets AS2225 requirements with glove ratings from 650V to 4000V
- ⇒ Natural latex base with straight cuff.
- ⇒ Economical Glove
- ⇒ Available in multiple sizes to suit most electrical applications.
- ⇒ Packaged in a UV resistant Opaque bag

### APPLICATIONS

- ⇒ Live Line Work, Switchboard Maintenance & any application requiring work with electricity between 650 & 4000 Volts



### TECHNICAL INFORMATION

Material: 100% Latex  
Lining: Non Flocked

### Recommendations for Use

- ⇒ Always define a voltage of use to select the adequate class of gloves from 650V to 4000V
- ⇒ Only wear tested and approved insulating gloves.
- ⇒ Do not use gloves older than 1 year from the date of manufacture without prior testing.
- ⇒ Before each use, conduct a visual inspection to check for cuts, nicks, holes and abrasions as well as inflating the glove with air to check for air leaks.

### Storage

- ⇒ Gloves must be stores at ambient temperature (10-21°C) in their original bag, away from direct sunlight, ozone or heat.

### STANDARDS

Approved to AS2225 Lic Number BMP 559940.

### ORDERING INFORMATION

| Part Number                       | Max. Use Voltage | Proof Test Voltage | Length | Size      | Colour | MOQ  | Pack Dim       |
|-----------------------------------|------------------|--------------------|--------|-----------|--------|------|----------------|
| <b>Latex Gloves—Straight Cuff</b> |                  |                    |        |           |        |      |                |
| 2091606                           | 650 V            | 5000 V             | 280mm  | 8,9,10,11 | BEIGE  | PAIR | 500 X 215 X 75 |
| 2091607                           | 650 V            | 5000 V             | 360mm  | 8,9,10,11 | BEIGE  | PAIR | 500 X 215 X 75 |
| 2091612                           | 1000 V           | 10,000 V           | 360mm  | 8,9,10,11 | BEIGE  | PAIR | 500 X 215 X 75 |
| 2091613                           | 1000 V           | 10,000 V           | 410mm  | 8,9,10,11 | BEIGE  | PAIR | 500 X 215 X 75 |
| 2091622                           | 3300 V           | 15,000 V           | 360mm  | 8,9,10,11 | BEIGE  | PAIR | 500 X 215 X 75 |
| 2091623                           | 3300 V           | 15,000 V           | 410mm  | 8,9,10,11 | BEIGE  | PAIR | 500 X 215 X 75 |
| 2091632                           | 4000 V           | 20,000 V           | 360mm  | 8,9,10,11 | BEIGE  | PAIR | 500 X 215 X 75 |
| 2091633                           | 4000 V           | 20,000 V           | 410mm  | 9,10,11   | BEIGE  | PAIR | 500 X 215 X 75 |

**WARNING!** THIS DOCUMENT PROVIDES AN OVERVIEW OF PERSONAL PROTECTIVE PRODUCTS AVAILABLE FROM HONEYWELL SAFETY PRODUCTS AND CARE HAS BEEN TAKEN TO ASSURE THE ACCURACY OF THE DATA. IT DOES NOT PROVIDE IMPORTANT PRODUCT WARNINGS AND INSTRUCTIONS. HONEYWELL SAFETY PRODUCTS RECOMMENDS ALL USERS OF ANY PERSONAL PROTECTIVE EQUIPMENT UNDERGO THOROUGH TRAINING, AND THAT ALL WARNINGS AND INSTRUCTIONS PROVIDED WITH THE PRODUCTS BE THOROUGHLY READ AND UNDERSTOOD PRIOR TO EACH USE. FAILURE TO READ AND FOLLOW ALL PRODUCT WARNINGS AND INSTRUCTIONS COULD RESULT IN SERIOUS INJURY.